

BRESENHAM'S LINE ALGORITHM

Bresenham Line (X_1, Y_1, X_N, Y_N):

Description: Here X_1 and Y_1 denote the starting x - coordinate and y - coordinate of the line and X_N and Y_N denote the ending x - coordinate and y - coordinate.

1. Set $D_X = X_N - X_1$ and $D_Y = Y_N - Y_1$
2. Set $D_i = 2D_Y - D_X$
3. Set $D_S = 2D_Y$ and $D_T = 2(D_Y - D_X)$
4. Call PutPixel(X_1, Y_1)
5. Repeat While ($X_1 < X_N$)
 6. Set $X_1 = X_1 + 1$
 7. If ($D_i < 0$) Then
 8. Set $D_i = D_i + D_S$
 9. Else
 10. Set $Y_1 = Y_1 + 1$
 11. Set $D_i = D_i + D_T$
 12. Call PutPixel(X_1, Y_1)
- [End of While]
13. Exit